



Стационарные генераторы серии G

По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72,
Астана+7(7172)727-132,
Белгород(4722)40-23-64,
Брянск(4832)59-03-52,
Владивосток(423)249-28-31,
Волгоград(844)278-03-48,
Вологда(8172)26-41-59,
Воронеж(473)204-51-73,
Екатеринбург(343)384-55-89,
Иваново(4932)77-34-06,
Ижевск(3412)26-03-58,
Казань(843)206-01-48,
Калининград(4012)72-03-81,
Калуга(4842)92-23-67,
Кемерово(3842)65-04-62,
Киров(8332)68-02-04,

Краснодар(861)203-40-90,
Красноярск(391)204-63-61,
Курск(4712)77-13-04,
Липецк(4742)52-20-81,
Магнитогорск(3519)55-03-13,
Москва(495)268-04-70,
Мурманск(8152)59-64-93,
Набережные Челны(8552)20-53-41,
Нижний Новгород(831)429-08-12,
Новокузнецк(3843)20-46-81,
Новосибирск(383)227-86-73,
Орел(4862)44-53-42,
Оренбург(3532)37-68-04,
Пенза(8412)22-31-16,
Пермь(342)205-81-47,
Ростов-на-Дону(863)308-18-15,

Рязань(4912)46-61-64,
Самара(846)206-03-16,
Санкт-Петербург(812)309-46-40,
Саратов(845)249-38-78,
Смоленск(4812)29-41-54,
Сочи(862)225-72-31,
Ставрополь(8652)20-65-13,
Тверь(4822)63-31-35,
Томск(3822)98-41-53,
Тула(4872)74-02-29,
Тюмень(3452)66-21-18,
Ульяновск(8422)24-23-59,
Уфа(347)229-48-12,
Челябинск(351)202-03-61,
Череповец(8202)49-02-64,
Ярославль(4852)69-52-93



SECURE AND RELIABLE



Briggs & Stratton® Home Standby Generators will keep you and your family secure during a sudden loss of power. With the ultimate in home power protection, we make sure that you are never left alone in the dark. Our Home Standby Generators are powered by Natural Gas (gas pipes) or Propane Gas (LPG gas bottle).

Watch the video to see why you will need a backup generator.



G60

Rated Power* LPG (Propane)	Rated Power* Natural Gas	Engine	Warranty
6kW	5.4kW	INTEK™ I/C® 500cc	2 years / 600 hours

PERFORMANCE

Rated Power (kW) LPG/NG	6 / 5.4
Rated Current (Amps) LPG/NG	39 / 35.3
Starting Watts LPG/NG*	8,900 / 8,100
Voltage (V) - Frequency (Hz)	230 - 50
Phase	Single
Power Factor	1.0

ENGINE

Engine Type	INTEK™ I/C® 500cc
Engine Capacity (cc)	500
Engine Speed (RPM)	3000
Fuel Type	Liquid Propane Gas / Natural Gas
Governor Type	Mechanical
Start Type	Automatic
Lubrication System	Full pressure
Oil Capacity (l)	1.4
Low Oil Pressure Sensor	Yes
Cooling System Type	Air-cooled

Fuel Consumption LPG (kg/h) @ 50% - 100% load	1.97 - 2.97
Fuel Consumption NG (m3/h) @ 50% - 100% load	2.66 - 3.43

OTHER FEATURES

Enclosure Materials	Galvanneal Steel
Overcrank Protection	Yes
Continuous Battery Charging	Yes
Sound level (dB) at 7m (50% Load)	72
Alternator	Brushed
Voltage Regulation	Automatic
Warranty	2 yrs / 600 hrs

* This generator is certified in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-04 (motors and generators).



G80

Rated Power* LPG (Propane)	Rated Power* Natural Gas	Engine	Warranty
8kW	6.5kW	Vanguard™ 570cc	3 years / 1000 hours

PERFORMANCE

Rated Power (kW) LPG/NG	8 / 6.5
Rated Current (Amps) LPG/NG	34.8 / 28.3
Starting Watts LPG/NG*	11,900 / 9,700
Voltage (V) - Frequency (Hz)	230 - 50
Phase	Single
Power Factor	1.0

ENGINE

Engine Type	Vanguard™ 570cc
Engine Capacity (cc)	570
Engine Speed (RPM)	3000
Fuel Type	Liquid Propane Gas / Natural Gas
Governor Type	Mechanical
Start Type	Automatic
Lubrication System	Full pressure
Oil Capacity (l)	1.7
Low Oil Pressure Sensor	Yes
Cooling System Type	Air-cooled
Fuel Consumption LPG (kg/h) @ 50% - 100% load	2.23 - 3.44
Fuel Consumption NG (m3/h) @ 50% - 100% load	3.14 - 4.79

OTHER FEATURES

Enclosure Materials	Galvanneal Steel
Overcrank Protection	Yes
Continuous Battery Charging	Yes
Sound level (dB) at 7m (50% Load)	67
Alternator	Brushed
Voltage Regulation	Automatic
Warranty	3 yrs / 1000 hrs

* This generator is certified in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-04 (motors and generators).



G110

Rated Power* LPG (Propane)	Rated Power* Natural Gas	Engine	Warranty
11kW	9.9kW	Vanguard™ 993cc	3 years / 1000 hours

PERFORMANCE

Rated Power (kW) LPG/NG	11 / 9.9
Rated Current (Amps) LPG/NG	49 / 43
Starting Watts LPG/NG*	14,000 / 12,700
Voltage (V) - Frequency (Hz)	230 - 50
Phase	Single
Power Factor	1.0

ENGINE

Engine Type	Vanguard™ 993cc
-------------	-----------------

Engine Capacity (cc)	993
Engine Speed (RPM)	3000
Fuel Type	Liquid Propane Gas / Natural Gas
Governor Type	Electronic
Start Type	Automatic
Lubrication System	Full pressure
Oil Capacity (l)	2.3
Oil Cooler	Yes
Low Oil Pressure Sensor	Yes
Cooling System Type	Air-cooled
Fuel Consumption LPG (kg/h) @ 50% - 100% load	3.01 - 4.83
Fuel Consumption NG (m3/h) @ 50% - 100% load	3.82 - 5.44

OTHER FEATURES

Enclosure Materials	Galvanneal Steel
Overcrank Protection	Yes
Continuous Battery Charging	Yes
Sound level (dB) at 7m (50% Load)	66.7
Alternator	Brushed
Voltage Regulation	Automatic
Warranty	3 yrs / 1000 hrs

* This generator is certified in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-04 (motors and generators).



G140



Rated Power* LPG (Propane)	Rated Power* Natural Gas	Engine	Warranty
14kW	12.6kW	Vanguard™ 993cc	3 years / 1000 hours

PERFORMANCE

Rated Power (kW) LPG/NG	14 / 12.6
Rated Current (Amps) LPG/NG	61 / 55.5
Starting Watts LPG/NG*	17,400 / 15,800
Voltage (V) - Frequency (Hz)	230 - 50
Phase	Single
Power Factor	1.0

ENGINE

Engine Type	Vanguard™ 993cc
Engine Capacity (cc)	993
Engine Speed (RPM)	3000
Fuel Type	Liquid Propane Gas / Natural Gas
Governor Type	Electronic
Start Type	Automatic
Lubrication System	Full pressure
Oil Capacity (l)	2.3
Oil Cooler	Yes
Low Oil Pressure Sensor	Yes
Cooling System Type	Air-cooled
Fuel Consumption LPG (kg/h) @ 50% - 100% load	3.41 - 5.3
Fuel Consumption NG (m3/h) @ 50% - 100% load	4.16 - 6.6

OTHER FEATURES

Enclosure Materials	Galvanneal Steel
Overcrank Protection	Yes
Continuous Battery Charging	Yes
Sound level (dB) at 7m (50% Load)	66.7
Alternator	Brushed
Voltage Regulation	Automatic
Warranty	3 yrs / 1000 hrs

* This generator is certified in accordance with UL (Underwriters Laboratories) 2200 (stationary engine generator assemblies) and CSA (Canadian Standards Association) standard C22.2 No. 100-04 (motors and generators).



Fully Automated, Quick Response and Durable.

Our permanently installed Briggs & Stratton® Backup Generator starts automatically seconds after sensing a power cut. The enclosures are made of rust-resistant durable Galvalume steel protecting the generators against damage caused by chipping and abrasions.



Losing electrical power in your own home can be very frustrating. Modern appliances such as lights, fridges, televisions and other electrical home devices need constant power to function. Many security systems also depend upon a reliable charge of energy to keep your family protected. Protect your home and family from the uncertainty of power outages by keeping the lights on and household appliances running.

Quiet and Reliable Backup Power.



The Briggs & Stratton® name is synonymous with dependability, and our backup generators are no exception. These generators, running on natural gas or propane bottle gas, are powered by professional Vanguard™ engines which are reliable and powerful.

Trust the Power®.



Make the switch.

Our backup generators operating with Briggs & Stratton® Automatic Transfer Switch** will ensure smooth changeover between the mains supply and the generator automatically.





По вопросам продаж и поддержки обращайтесь:

Архангельск (8182)63-90-72,
Астана+7(7172)727-132,
Белгород(4722)40-23-64,
Брянск(4832)59-03-52,
Владивосток(423)249-28-31,
Волгоград(844)278-03-48,
Вологда(8172)26-41-59,
Воронеж(473)204-51-73,
Екатеринбург(343)384-55-89,
Иваново(4932)77-34-06,
Ижевск(3412)26-03-58,
Казань(843)206-01-48,
Калининград(4012)72-03-81,
Калуга(4842)92-23-67,
Кемерово(3842)65-04-62,
Киров(8332)68-02-04,

Краснодар(861)203-40-90,
Красноярск(391)204-63-61,
Курск(4712)77-13-04,
Липецк(4742)52-20-81,
Магнитогорск(3519)55-03-13,
Москва(495)268-04-70,
Мурманск(8152)59-64-93,
Набережные Челны(8552)20-53-41,
Нижний Новгород(831)429-08-12,
Новокузнецк(3843)20-46-81,
Новосибирск(383)227-86-73,
Орел(4862)44-53-42,
Оренбург(3532)37-68-04,
Пенза(8412)22-31-16,
Пермь(342)205-81-47,
Ростов-на-Дону(863)308-18-15,

Рязань(4912)46-61-64,
Самара(846)206-03-16,
Санкт-Петербург(812)309-46-40,
Саратов(845)249-38-78,
Смоленск(4812)29-41-54,
Сочи(862)225-72-31,
Ставрополь(8652)20-65-13,
Тверь(4822)63-31-35,
Томск(3822)98-41-53,
Тула(4872)74-02-29,
Тюмень(3452)66-21-18,
Ульяновск(8422)24-23-59,
Уфа(347)229-48-12,
Челябинск(351)202-03-61,
Череповец(8202)49-02-64,
Ярославль(4852)69-52-93